DISIBEINT	www.microlectra.nl info@micro	rolectra.nl
	B B ER	
Difference	Multifunction - Multirange - Monovoltage	
Operating principie	<ul> <li>10 modes according to the "FUNCTION" selector (see description of the func</li> <li><u>Without using the external input:</u> <ul> <li>A - Delay on operate</li> <li>B - Interval on operate</li> </ul> </li> <li>2 Using the external input: <ul> <li>A - Delay on operate, with time storage, without memory</li> <li>B - Interval on operate, with time storage, without memory</li> <li>C - Delay on operate, when the input is activated</li> <li>D - Interval on operate, when the input is activated</li> <li>E - Delay on operate, when the input is deactivated</li> <li>F - Interval on operate, when the input is deactivated</li> <li>G - Delay on operate, when the input is deactivated</li> <li>H - Interval on operate, when the input is activated and when it is deactivated</li> </ul> </li> </ul>	tions at page 2): ated vated
Time range	From 10 ms to 100 h, divided in 8 ranges (see table Reference).	
Leds indications	Power on: Green Relay on: Red	
Repeating precision	± 0,02%	
Precision	± 0,6%. With supply voltages 901 or 902, ± 1,2%.	
Power on	< 100 ms	
Reset External input	<ul> <li>By disconnecting the supply for longer than 20 ms</li> <li>Free potential contact (terminals 6-7 [PTMx]; Y1-Z1 [DTMx]).</li> <li>Sensor NPN or PNP, 10 mA / 24 VDC (terminals 5-6-7 [PTMx]; Y1-Z1-Z2 [DT Minimum pulses frequency: 6 ms</li> </ul>	Mx]).
Adjustment mode	<ul> <li>1<sup>st</sup> - Select the function.</li> <li>2<sup>nd</sup> - Select the range. The maximum value (top of scale) must be the ne time you are going to set.</li> <li>3<sup>rd</sup> - Set the time according to the 0-10 relative scale.</li> <li>Example: If you want to set 45 seconds, select the range "10100 s". In the corresponds to 9 seconds, so you must place the "TIME" button in the "5 to check the time and refine the adjustment if required.</li> </ul>	arest possible to the is case each division ". It is recommended

To compose the reference, select one option of each column. Example: PTMA U40 100



## WITHOUT USING THE EXTERNAL INPUT

## Delay on operate

When the supply voltage is connected the relay remains released and the time circuit starts up. Once the preset time is elapsed, the relay operates and remain so for an undefined time





## Interval on operate

When the supply voltage is connected the relay operates immediately and the time circuit starts up. Once the preset time is elapsed, the relay releases and remain so for an undefined time.

La Tan	in the	

## DELAY ON OPERATE, USING THE EXTERNAL INPUT

#### With time storage, without memory

When the supply voltage is connected the relay remains released and the time circuit starts up. If the external input is activated before the preset time is elapsed, the time circuit stops. When the input is released, the time circuit follows from the point where it stopped previously. When the time accumulated is greater than the preset time, the relay operates and remains so for an undefined time.

The absence of power supply causes the time and relay reset.



### While the input is activated

When the supply voltage is connected, if the external input is not activated there is no effect on the system. When the input is activated the time circuit starts up. Once the preset time is elapsed, the relay operates and remains so until the external input or the supply voltage are deactivated.

The succession of input pulses with a cadence less than the preset time brings about the reset of the time.



## When the input is deactivated

When the supply voltage is connected there is no effect on the system regardless of the state of the external input. When the input is activated, the relay remains released and when it is deactivated the time circuit starts up. Once the preset time is elapsed, the relay operates and remains so until the input is again activated or the supply voltage is disconnected.

The succession of input pulses with a cadence less than the preset time brings about the reset of the time.



# When the input is activated and when it is deactivated

When the supply voltage is connected there is no effect on the system regardless of the state of the external input. When the input is activated, the relay remains released and the time circuit starts up. Once the preset time is elapsed, the relay operates. When the input is deactivated, the relay releases and the time circuit starts up again. Once the preset time is elapsed, the relay operates.

The succession of input pulses with a cadence less than the preset time brings about the reset of the time

# INTERVAL ON OPERATE, USING THE EXTERNAL INPUT

#### With time storage, without memory

When the supply voltage is connected the relay operates immediately and the time circuit starts up. If the external input is activated before the preset time is elapsed, the time circuit stops. When the input is released, the time circuit follows from the point where it stopped previously. When the time accumulated is greater than the preset time, the relay releases and remains so for an undefined time.

The absence of power supply causes the time and relay reset.



When the supply voltage is connected, if the external input is not activated there is no effect on the system. When the input is activated the relay operates immediately and the time circuit starts up. Once the preset time is elapsed, the relay releases and remains so until the external input is again activated.

The succession of input pulses with a cadence less than the preset time brings about the reset of the time.



DEF

DE

## When the input is deactivated

When the supply voltage is connected, if the external input is not activated there is no effect on the system. When the input is activated the relay operates immediately and when it is deactivated the time circuit starts up. Once the preset time is elapsed, the relay releases and remains so until the external input or the supply voltage are deactivated. The succession of input pulses with a cadence less than the preset time brings about the reset of the time.

#### When the input is activated and when it is deactivated

When the supply voltage is connected there is no effect on the system regardless of the state of the external input. When the input is activated, the relay operates immediatley and the time circuit starts up. Once the preset time is elapsed, the relay releases. When the input is deactivated, the relay operates and the time circuit starts up again. Once the preset time is elapsed, the relay releases.

The succession of input pulses with a cadence less than the preset time brings about the reset of the time.



















ľ			PTMA	РТМВ	DTMA	DTMB	
			660 6 8 8 0 0 0 0 0		16 18	16 18 26 28	
		AC	10 A / 250 V	8 A / 250 V	10 A / 250 V	8 A / 250 V	
	Resistive load	DC	0,4 A / 200 V	0,25 A / 200 V	0,4 A / 200 V	0,25 A / 200 V	
s		DC	10 A / 24 V	8 A / 24 V	10 A / 24 V	8 A / 24 V	
iay		AC	5 A / 250 V	2,5 A / 250 V	5 A / 250 V	2,5 A / 250 V	
1 e	Inductive load	DC	5 A / 24 V	4 A / 24 V	5 A / 24 V	4 A / 24 V	
срu	Mechanical life		> 30 x 10 <sup>6</sup>	operations	> 30 x 10 <sup>6</sup> operations		
5 C	Max. switching rate, mech.		72.000 operations / hour		72.000 operations / hour		
	Electrical life at full load		360 operations / hour		360 operations / hour		
	Contact material		AgNi 90/10		AgNi 90/10		
	Maximum voltage		440 VAC		440 VAC		
	Operating voltage		250 VAC		250 VAC		
	Volt. between changeovers		2500 VAC		2500 VAC		
	Voltage between contacts		1000 VAC		1000 VAC		
	Voltage coil/contact		5000 VAC		5000 VAC		
	Distance	coil/contact	10	mm	10 mm		
	Isolation	n resistance	> 10	0 <sup>4</sup> MΩ	> 10⁴ MΩ		

		A	C	D	с	AC	DC
		PTMA / PTMB	DTMA / DTMB	PTMA / PTMB	DTMA / DTMB	PTMA / PTMB	DTMA / DTMB
pply		000 000 000 000 000	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~			°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°°	
ŝ	Galvanic isolation	400	00 v	N	lo	9XX: 2500 v	~ UXX: No
	Consumption	1,6 VA 50/60 Hz ± 15%		1,2	2 W	9XX: 1,6 W	~ UXX: 1,7 W
	Frequency				-		-
	Operating margins			± 1	0%		-
	Positive		-	Terminal 2	Terminal A1	Terminal 2	Terminal A1
	Protected polarity		-	Ye	es	Y	es

		PTMA/PTMB	DTMA/DTMB
constructive and anviromental data	Voltage phase-neutral	300 V	300 V
	Overvoltage category	111	111
	Rated impulse voltage	4 kV	4 kV
	Pollution degree	2	2
	Protection	IP 20 B	IP 20
	Approximate weight	250 g	280 g
	Storage temperature	-50°C+85°C	-50°C+85°C
	Operating temperature	-20°C+50°C	-20°C+50°C
	Humidity	3085% HR	3085% HR
	Housing	Cycoloy - Light grey	Cycoloy - Light grey
	Socket	Lexan - Light grey	-
	Leds cover	Lexan - Transparent	Lexan - Transparent
	Button, terminal block, clip	Technyl - Dark blue	Technyl - Dark blue
	Pins of the socket	Nickel brass	-
	Pins of the terminal block	-	Brass
0	Approvals	Designed and manufactured under EEC	standards.Electromagnetic compatibility

Designed and manufactured under EEC standards.Electromagnetic compatibility, directive **EMC 2004/108/CEE** (UNE-EN 61000 6-4/2007/A1:2011, UNE-EN 61000 6-2/2006). Electric safety, directive **LVD 2006/95/CEE** (UNE-EN-60204-1/2007/A1:2009; UNE-EN 61010-1/2011). Directive about certain hazardous sustances **2011/65/CEE** de 8/06/2011 Pb, Hg, Cd, Cr+6, PBB, PBDE. Plastics: **UL 91 V0**.



 $Rev.\,02/00\,\cdot\,15/12/16\,\cdot\,DISIBEINT\ reserves\ the\ right\ to\ modify\ the\ specifications\ stated\ in\ this\ document\ without\ previous\ notice$ 



Microlectra bv. Augustapolder12 2992 SR Barendrecht. The Netherlands